



1-5/8" RADIAFLEX® RLKU Cable, A-series

Product Description

RADIAFLEX® functions as a distributed antenna to provide communications in tunnels, mines and large building complexes and is the solution for any application in confined areas.
 Slots in the copper outer conductor allow a controlled portion of the internal RF energy to be radiated into the surrounding environment. Conversely, a signal transmitted near the cable will couple into the slots and be carried along the cable length.
 RADIAFLEX® is used for both one-way and two-way communication systems and because of its broadband capability, a single radiating cable can handle multiple communication systems simultaneously.
 This RADIAFLEX® radiating cable utilize a low-loss cellular polyethylene foam dielectric and a smooth copper outer conductor which offers a superior electrical performance together with good bending properties.



RLK cable, A-series

Features/Benefits

- Ultra wideband from 30 MHz to 2700 MHz
- For applications in tunnels and buildings
- Low coupling loss variations
- Lowest insertion loss and excellent coupling performance to minimize count of active equipment
- Best-in-class, RF ultra wideband radiating cable, accomodating all current and future commercial radio and private radio service from 30 MHz to 2700 MHz

Technical Specifications

Size:	[in]	1-5/8"
Max. operating frequency:	[MHz]	2700
Cable Type:		RLK
Jacket	JFN: halogen free, non corrosive, flame and fire retardant, low smoke, polyolefin Test methods for fire behaviour of cable : IEC 60754-1/-2 smoke emission: halogen free, non corrosive IEC 61034 low smoke IEC 60332-1 flame retardant IEC 60332-3-24 fire retardant	
Slot Design	Groups of vertical slots at short intervals	
Previous Model Number		
Impedance	[Ω]	50 +/-2
Relative propagation velocity	[%]	89
Capacitance	[pF/m (pF/ft)]	76 (23.2)
Inductance	[μH/m (μH/ft)]	0.190 (0.058)
DC-resistance inner conductor	[Ω/km (Ω/1000ft)]	1.30 (0.40)
DC-resistance outer conductor	[Ω/km (Ω/1000ft)]	1.30 (0.40)
Outer Conductor Material	Overlapping Copper Foil	
Inner Conductor Material	Corrugated Copper Tube	
Diameter over Jacket	[mm (in)]	48.2 (1.90)
Diameter Outer Conductor	[mm (in)]	44.2 (1.74)
Diameter Inner Conductor	[mm (in)]	17.6 (0.69)
Minimum Bending Radius, Single Bend	[mm (in)]	700 (28.0)
Cable Weight	[kg/m (lb/ft)]	1.10 (0.74)
Max. tensile force	[N (lb)]	1200 (270)
Indication of Slot Alignment	Guides opposite to slots	
Storage temperature	[°C (°F)]	-70 to +85 (-94 to +185)
Installation temperature	[°C (°F)]	-25 to +60 (-13 to +140)
Operation temperature	[°C (°F)]	-40 to +85 (-40 to +185)
Stop bands	[MHz]	540-610
Recommended / maximum clamp spacing	[m (ft)]	1.5 (5)
Minimum Distance to Wall	[mm (in)]	80 (3.15)
Length	[m (ft)]	

Frequency, MHz	Longitudinal Loss, dB/100 m (dB/100 ft)	Coupling Loss 50%, dB	Coupling Loss 95%, dB
75	0.55 (0.17)	70 (75)	78 (82)
150	0.81 (0.25)	70 (75)	78 (82)
500	1.60 (0.49)	70 (72)	79 (80)
700	2.00 (0.61)	69 (71)	71 (74)
800	2.17 (0.66)	67 (71)	68 (73)
870	2.29 (0.70)	67 (72)	69 (74)
900	2.32 (0.71)	68 (72)	70 (75)
960	2.43 (0.74)	66 (70)	69 (73)
1700	3.57 (1.09)	65 (69)	70 (74)
1800	3.70 (1.13)	62 (66)	65 (70)
1900	3.95 (1.20)	62 (66)	65 (70)
2000	4.15 (1.27)	63 (67)	67 (72)
2100	4.41 (1.34)	62 (66)	66 (71)
2200	4.62 (1.41)	62 (66)	66 (71)
2400	5.18 (1.58)	63 (68)	67 (71)
2600	5.80 (1.77)	61 (65)	64 (68)
2700	5.96 (1.82)	63 (66)	67 (70)

Standard conditions

Notes

- Coupling loss as well as longitudinal attenuation of RADIAFLEX® cables are measured by the free space method according to IEC 61196-4.
- Coupling loss values are measured with a radial (below 540 MHz) or parallel (above 610 MHz) orientated dipole antenna.
- The coupling loss values given in brackets are average values of all three spatial orientations (radial, parallel and orthogonal) of dipole antenna.
- Coupling loss values are given with a tolerance of ±5 dB and longitudinal loss values with a tolerance of ±5%.
- In case of a conflict of operational and stop band, please contact RFS for further assistance.
- As with any radiating cable, the performance in building or tunnel environments may deviate from figures based on free space method.

Rev.

2010/09/28

All information contained in the present datasheet is subject to confirmation at time of ordering